

SPECIFICATIONS:

260W Mixing Amplifier have DVD Remote control
1. With 5CH MIC input, 1CH AUX input; individual volume control.

2. High impedance output and low impedance output.

3. Support mixing input plug that $\varphi 6.3\text{m/m}$ unbalance.

4. Supplied LED VU indicator.

5. MIC 1 with broadcast priority and can automatic cut input source.

6. Two independent tone controls.

7. Rated Output Power : 260W.

8. Input:

MIC Input * 5CH 2mv-54dB at 10K Ω .

AUX Input * 1CH 90mv-22dB at 100K Ω .

9. Output Impedance:

Low impedance output 0, 4 ohms, 8 ohms, 16ohms.

High impedance output 70V, 100V.

10. Output Indication: LED Level Meter.

11. Tone Control: Bass +/-10dB at 100Hz ; Treble +/-10dB at 10KHz.

12. REC Output: LINE OUT 500mv.

13. Frequency Response: 25Hz ~ 18 KHz +/-3dB.

14. AC Power Source: AC220V~AC240V.

15. Weight: 10.4kg / 11.6kg / 15.7kg / 17.2kg.

16. Dimensions: 430W * 355D * 133H(mm).

DVD function

1. CD-ROM media corresponds:

DVD/SVCD/VCD/CD-R/-
RW/DVCD/HDCD/MP3/MPGE4

2. Display: do not display track number and song, with Repeat, FF, RF, PLAY, STOP, PAUSE.

3. With USB devices.

4. With the EQ function.

5. with a remote control.

**HAN 260CD
Mixing Amplifier**