

SPECIFICATIONS:

40W Mixing Amplifier have MP3 USB Remote control

1. With 2CH MIC input, 1CH AUX input; individual volume control.
2. 4 ohms - 16 ohms low impedance output.
3. Support mixing input plug that $\varphi 6.3\text{m/m}$ unbalance.
4. with mini rack-typed box design, suitable for car amplifier use.
5. Rated Output Power: 40W.
6. Input: MIC Input * 2CH; AUX Input * 1CH.
7. Output Impedance: 4 ohms - 16 ohms.
8. Indication: Power LED Indication.
9. Tone Control: Bass +/-10dB ; Treble +/-10dB.
10. Weight: 2kg.
11. Dimensions: 260W * 155D * 80H(mm).

MP3 / USB function

1. Can read the USB interface of the MP3 music format, has also played dual USB functions.
2. SD CARD interface can read the MP3 music format, while playing with dual SD function.
3. Has aired song, single, multi-curved-dash features.
4. Convenient, easy selections play / pause, reset operation.
5. Are free to choose any of a group of players.
6. With linked selection, when the first group play is completed, for cutting the second group can be Directly broadcast group 2.
7. At least 2G memory card support.
8. Has a separate audio output.
9. With mixed audio output.
10. Messages with a digital display.
11. With a SD card or USB card, select the function key.
12. Duplicate keys with REPEAT / EQ / PREV VOL-(on the first) / NEXT VOL + (Next) /

HAP 40 /40W - Mixing Amplifier

PLAY PAUSE (Play / Pause) and other function keys.

13. Has a volume control.
14. with a volume meter.
15. with 10-band EQ adjustment.

